

 Model Number
 DOC NO

 3055D5
 PERFORMANCE SPECIFICATIONS
 PS3055D5

 IEPE ACCELEROMETER
 REV.E. ECN. 12776, 06/24/16



- HERMETICALLY SEALED
- BASE ISOLATED
- IDEAL LOW FREQUENCY RESPONSE

		ENGLI	СП	SI	
PHYSICAL		ENGLI	оп	31	
		0.35		10] arama
Weight Connector	T	10-32	OZ	10-32	grams
Mounting Provision	Type Tapped Hole	10-32 10-32 X .150 ↓		10-32 X .150 ↓	1
•	гаррей гюје	Titanium		Titanium	•
Material, Housing/Connector Sensing Element		Ceramic		Ceramic	•
Element Style		Planar Shear		Planar Shear	}
PERFORMANCE					
Sensitivity, ± 5% [1]		20	mV/g	2	mV/m/s ²
Range for ± 5 Volts Output		250	g	2453	m/s ²
Frequency Response, ± 10%		1 to 10000	Hz	1 to 10000	Hz
Resonant Frequency		> 36	kHz	> 36	kHz
Broad Band Resolution		0.0020	Grms	0.020	m/s ² rms
Linearity [2]		±1	% F.S.	±1	% F.S.
Maximum Transverse sensitivity		5	%	5	%
Strain Sensitivity @ 250με		0.002	g/με	0.02	m/s²/με
ENVIRONMENTAL					
Maximum Vibration		600	Gpeak	5886	m/s² peak
Maximum Shock		2000	Gpeak	19620	m/s² peak
Temperature Range		-67 to +250	°F	-55 to 121	°C
Seal		Hermetic		Hermetic]
ELECTRICAL					
Supply Current Range [3]		2 to 20	mA	2 to 20	mA
Compliance Voltage Range		18 to +30	Volts	18 to +30	Volts
Output Impedence,Typ		100	Ω	100	Ω
Bias Voltage		11 to 13	VDC	11 to 13	VDC
Discharge Time Constant		0.5 to 1.5	Sec	0.5 to 1.5	Sec
Electrical Isolation		10	GΩ,min	10	GΩ,min
					1

This family also includes:								
Model		Sensitivity (mV/g)	Frequency Response (Hz)	Time Constant (Sec)	Operating Temp (°F)			
3055D1	ı	10	1 to 10000	0.5 to 1.5	-67 to +250			
3055D2	2	100	1 to 10000	0.5 to 1.5	-67 to +250			
3055D3	3	500	1 to 10000	0.5 to 1.5	-67 to +225			
3055D4	1	50	1 to 10000	0.5 to 1.5	-67 to +250			
3055D6	6	200	1 to 10000	0.5 to 1.5	-67 to +225			

Refer to the performance specifications of the products in this family for detailed description

Supplied Accessories:

- 1) Accredited calibration certificate (ISO 17025)
- 2) Model 6200 mounting stud, qty 1

Notes:

- [1] Measured at 100Hz, 1 Grms per ISA RP 37.2.
- [2] Measure using zero-based straight line method, % of F.S. or any lesser range.
- [3] Do not apply power to this system without current limiting, 20 mA MAX. To do so will destroy the IC charge amplifier.
- [4] In the interest of constant product improvement, we reserve the right to change specifications without notice.



