

 Model Number
 DOC NO

 3256A3T
 PERFORMANCE SPECIFICATIONS
 PS3256A3T

 IEPE ACCELEROMETER
 Rev A, ECN 11835, 05/22/15



- HERMETICALLY SEALED
- CASE GROUNDED
- TEDS

		ENGLISH		SI	
PHYSICAL			•		i
Weight		0.35	OZ	10	grams
Connector	Туре	10-32		10-32	
Mounting Provision	Tapped Hole	10-32 X .150 ↓		10-32 X .150 ↓	
Material, Housing/Connector		Titanium		Titanium	
Sensing Element		Ceramic		Ceramic	
Element Style		Planar Shear		Planar Shear	
PERFORMANCE					
Sensitivity, ±5% [1]		500	mV/G	51.0	mV/m/s ²
Range for ± 5 Volts Output		10	G peak	98	m/s ²
Frequency Response, ±10%		1 to 10,000	Hz	1 to 10,000	Hz
Resonant Frequency		> 36	kHz	> 36	kHz
Broad Band Resolution		0.0004	G rms	0.0039	m/s ² rm
inearity [2]		±1	% F.S.	±1	% F.S.
Maximum Transverse Sensitivity		5	%	5	%
Strain Sensitivity @ 250με		0.001	G/με	0.01	m/s²/με
ENVIRONMENTAL					
Maximum Vibration		200	G peak	1962	m/s² pea
Maximum Shock		1000	G peak	9810	m/s ² pea
Operating Temperature Range		-60 to +225	°F	-51 to 107	°C
TEDS Operating Temperature		-40 to +185	°F	-40 to +85	°C
Seal		HERMETIC		HERMETIC	
ELECTRICAL					
Supply Current Range [3]		2 to 20	mA	2 to 20	mA
Compliance Voltage Range		+18 to +30	Volts	+18 to +30	Volts
Output Impedence, Typ		100	Ω	100	Ω
Bias Voltage		+9 to +13	VDC	+9 to +13	VDC
Discharge Time Constant		.5 to 1.5	Sec	.5 to 1.5	Sec
TEDS		IEEE 1451.4		IEEE 1451.4	230

This family also includes:								
Model	Sensitivity (mV/g)	Frequency Response (Hz)	Time Constant (Sec)	Operating Temp (°F)				
3256A1T	10	1 to 10000	0.5 to 1.5	-60 to +250				
3256A3T	500	1 to 10000	0.5 to 1.5	-60 to +225				
3256A5T	50	1 to 10000	0.5 to 1.5	-60 to +250				


Refer to the performance specifications of the products in this family for detailed description


Supplied Accessories:


- 1) Accredited calibration certificate (ISO 17025)
- 2) 10-32 to 10-32 mounting stud, Model 6200. Qty. 1

Notes:

- [1] Measured at 100Hz, 1 Grms per ISA RP 37.2.
- [2] Measured using zero-based straight line method, % of F.S. or any lesser range.
- [3] Do not apply power to this system without current limiting, 20 mA MAX. To do so will destroy the IC charge amplifier.
- [4] In the interest of constant product improvement, we reserve the right to change specifications without notice.







_

