

 Model Number 1060V6
 PEFORMANCE SPECIFICATION
 Doc No PS1060V6

 Force Sensors, IEPE
 REV C, ECN 15099, 06/03/19



- DYNAMIC FORCE SENSOR
- VOLTAGE MODE
- EXCELLENT LINEARITY

	ENGLISH		SI	
PHYSICAL	-	•	-	
Weight, Max.	16.10	oz	460	grams
Connector Type	Coaxial		Coaxial	
Thread	10-32		10-32	
Housing Material	Stainless steel		Stainless steel	
Isolation	Case grounded		Case grounded	
Sensing Element Material	Quartz		Quartz	
Mode	Compression		Compression	
PERFORMANCE				
Sensitivity, +/-10%	0.1	mV/Lb	0.02	mV/N
Compression Range	50000	Lbs.Force	222400	N
Maximum Compression , +/-5%	60000	Lbs.Force	266880	N
Tension Range	1000	Lbs.Force	4448	N
Maximum Tension [1], +/-5%	1000	Lbs.Force	4448	N
Resolution	0.70	Lb. RMS	3.11360	N RMS
Linearity [2]	± 1	% Full Scale	± 1	% Full Scale
Mounted Resonance (Unloaded)	≥ 75	kHz	≥ 75	kHz
Stiffness	50	Lb/µin	8.66	kN/μm
ENVIRONMENTAL				
Coefficient Of Thermal Sensitivity	0.03	%/°F	0.05	%/°C
Operating Temperature	-100 to +250	°F	-73 to +121	°C
Maximum Vibration	±3000	g's,Peak	±29400	m/s^2 Peak
Maximum Shock	5,000	g's,Peak	49,000	m/s^2 Peak
Environmental Seal	Ероху		Ероху	
ELECTRICAL				
Supply Current [3]	2 to 20	mA	2 to 20	mA
Compliance Voltage	+18 to +30	VDC	+18 to +30	VDC
Discharge Time Constant, Min.	2000	Seconds	2000	Seconds
F.S. Output Voltage	5	Volts	5	Volts
Output Impedance	100	Ω	100	Ω

This family also includes:						
Model	Sensitivity (mV/Lb)	Range (LbsF) Compressive, Tensile	Max Force (LbsF) Compressive, Tensile	Discharge Time Constant (Sec)		
1060V1	10	500, 500	10000, 1000	150		
-1060V2	5	1000, 1000	20000, 1000	<del>300</del>		
1060V3	1	5000, 1000	30000, 1000	1500		
1060V4	0.5	10000, 1000	40000, 1000	2000		
1060V5	0.2	25000, 1000	50000, 1000	2000		


Refer to the performance specifications of the products in this family for detailed description


## Supplied Accessories:

- 1) Accredited Calibration Certificate (ISO 17025)
- 2) MOD 6232 MOUNTING STUD

## Notes:

- [1] Absolute maximum tension. Do not exceed in any case!
- [2] Percent of full scale or any lesser range, zero based best-fit sraight line method.
- [3] Power these instruments only with constant current type power units. Do not connect to a source of voltage without current limiting. This will destroy the integral IC amplifier.
- [4] In the interest of constant product improvement, we reserve the rights to change the specifications without notice. It is the customer's responsibility to validate that a particular product with the properties described in the product specification is suitable for use in a particular application. Parameters provided in datasheets and / or specifications may vary in different applications and performance may vary overtime. All operating parameters, including typical parameters, must be validated for each customer application by the customer's technical experts.





Units on the line drawing are in inches, units in brackets are in millimeters. Refer to 127-1060V for more information.

